

TravelMate 24	10 Quick Spec
Operating system <sup>1</sup>	Microsoft <sup>®</sup> Windows <sup>®</sup> XP Home Edition (Service Pack 2)
	Microsoft <sup>®</sup> Windows <sup>®</sup> XP Professional (Service Pack 2)
Platform <sup>1</sup>	Intel <sup>®</sup> Celeron <sup>®</sup> M processor 360/370/380 (1 MB L2 cache, 1.40/1.50/1.60 GHz, 400 MHz FSB)
	Intel <sup>®</sup> 910GML chipset
System memory	256/512 MB of DDR2 400 memory, upgradeable to 2 GB using two soDIMM modules
Display and graphics	15.4" WXGA color TFT LCD, 1280 x 800 pixel resolution, supporting simultaneous multi-window viewing on dual displays via Acer GridVista
	15" XGA color TFT LCD, 1024 x 768 pixel resolution
	16.7 million colors
	Intel <sup>®</sup> 910GML integrated 3D graphics featuring Intel <sup>®</sup> GMA 900 with up to 128 MB of shared memory
	Microsoft <sup>®</sup> DirectX <sup>®</sup> 9.0 support
	Dual independent display support
	Simultaneous LCD and CRT display, with LCD panel resolution at 70 Hz
	External resolution/refresh rate:
	• 2048 x 1536: 75/60 Hz
	• 1600 x 1200: 120/100/85/75/60 Hz
	• 1400 x 1050: 60 Hz
	• 1280 x 1024: 160/120/100/85/75/60 Hz
	• 1024 x 768: 200/160/120/100/85/75/60 Hz
	• 800 x 600: 200/160/120/100/85/75/60 Hz
	MPEG-2/DVD hardware-assisted capability
Storage	40/60/80 GB ATA/100 hard disk drive
subsystem <sup>1</sup>	Choice of:
	• DVD-Dual double-layer
	• DVD/CD-RW combo
	Disk performance compatibility
	• DVD-Dual double-layer

TravelMate 2410 Quick Spec		
	-Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 8X DVD+R, 8X DVD-R, 6X DVD+RW, 6X DVD-RW, 4X DVD+R (double-layer)	
	-Write: 24X CD-R, 16X CD-RW, 8X DVD+R, 8X DVD-R, 4X DVD+RW, 4X DVD-RW, 2.4X DVD+R (double-layer)	
	• DVD/CD-RW combo	
	-Read: 24X CD-ROM, 24X CD-R, 15X CD-RW, 8X DVD-ROM, 4X DVD+R, 4X DVD-R, 4X DVD+RW, 4X DVD-RW	
	-Write: 24X CD-RW, 24X CD-R	
Dimensions and weight <sup>1</sup>	363 (W) x 275 (D) x 24/32.9 (H) mm (14.29 x 10.83 x 0.94/1.3 inches) 2.74kg (6.04 lbs) for 15" LCD model	
	2.75kg (6.06 lbs) for 15.4" LCD model	
Power subsystem	ACPI 2.0 power management standard: supports Standby and Hibernation power-saving modes	
	29.6 Li-ion battery pack <sup>1</sup>	
	2.1-hour battery life (4-cell) <sup>1</sup>	
	2.5-hour rapid charge; 3.5-hour charge-in-use	
	65 W AC adapter	
Input devices	<pre>88-/89-key Acer FineTouch<sup>™</sup> keyboard with 5-degree curve, inverted "T" cursor layout, international language support, 2.5 mm (minimum) key travel</pre>	
	Touchpad with 4-way scroll button	
	12 function keys, four cursor keys, two Windows <sup>®</sup> keys, hotkey controls, embedded numeric keypad	
	Four easy-launch buttons: Internet, email, Empowering Key and one user-programmable button	
	Front-access LED-buttons	
Audio	Audio system with two built-in speakers	
Audio		
Audio	Audio system with two built-in speakers Sound Blaster Pro <sup>™</sup> and MS-Sound compatible Built-in microphone	
Audio Communication	Audio system with two built-in speakers Sound Blaster Pro <sup>™</sup> and MS-Sound compatible	
	Audio system with two built-in speakers Sound Blaster Pro <sup>™</sup> and MS-Sound compatible Built-in microphone Modem: 56K ITU V.92 with PTT approval <sup>2</sup> ;	
	Audio system with two built-in speakers Sound Blaster Pro <sup>™</sup> and MS-Sound compatible Built-in microphone Modem: 56K ITU V.92 with PTT approval <sup>2</sup> ; Wake-on-Ring ready	
	Audio system with two built-in speakers Sound Blaster Pro <sup>™</sup> and MS-Sound compatible Built-in microphone Modem: 56K ITU V.92 with PTT approval <sup>2</sup> ; Wake-on-Ring ready LAN: 10/100 Mbps Ethernet; Wake-on-LAN ready WLAN <sup>1</sup> : integrated Acer InviLink <sup>™</sup> 802.11b/g Wi-Fi CERTIFIED <sup>™</sup> network solution, supporting Acer	

## TravelMate 2410 Quick Spec

TravelMate 2410 Quick Spec		
	External display (VGA) port	
	Headphones/speakers/line-out port	
	Microphone/line-in jack	
	Ethernet (RJ-45) port	
	Modem (RJ-11) port	
	DC-in jack for AC adapter	
Security	Kensington lock slot	
	BIOS user and supervisor passwords	
Software	Acer eManager (ePowerManagement, ePresentation, eRecovery <sup>3</sup> and eSettings)	
	Acer GridVista 2.0 <sup>4</sup>	
	Acer Launch Manager	
	Norton AntiVirus <sup>™</sup>	
	Adobe <sup>®</sup> Reader <sup>®</sup>	
	CyberLink® PowerDVD <sup>™</sup>	
	NTI CD-Maker™	
Options and	8-cell Li-ion battery pack	
accessories	65 W AC adapter	
	256/512 MB or 1 GB DDR2 533 MHz soDIMM modules	
	External USB floppy disk drive	
System compliance	ACPI 2.0	
	ENERGY STAR <sup>®</sup>	
	Mobile PC 2002	
	DMI 2.0	
	Microsoft MDA 2005/2006	
	Wi-Fi®	
	Cisco Compatible Extensions (CCX) <sup>5</sup>	
Warranty	One-year International Travelers Warranty (ITW)	
Quality and reliability tests	Temperature and humidity	
	Hinge life	
	Weight and pressure	
	Acoustics	
	Spillage	
	Free drop	
	Shock and vibration	
	Electrostatic discharge immunity	

TravelMate 2410 Quick Spec		
	Keyboard-switch life	
	MTBF (mean time between failures)	
made intel	Acer recommends Microsoft <sup>®</sup> Windows <sup>®</sup> XP Professional.	
pentium celeron	<ol> <li>Specifications vary depending on model and usage.</li> </ol>	
Designed for Microsoft® Windows®XP	2. PTT countries: Asia: China, Hong Kong, Japan, Korea, Malaysia, Singapore, Taiwan. Europe: Austria, Belgium, Denmark, Finland, France, Germany, Greece, Holland, Iceland, Italy, Luxembourg, Norway, Portugal, Spain, Sweden, Switzerland. Oceania: Australia, New Zealand. N. America: Canada, USA.	
	<ol> <li>This feature uses 2 to 3 GB of hard disk space.</li> </ol>	
WE SELL ENERBY STAR	<ol> <li>Acer GridVista is bundled with 15.4" widescreen models only.</li> </ol>	
	5. Supports Cisco Compatible Extensions Version 3.0 (CCX-V3)	
	In a continuing effort to improve the quality of our products, information in this brochure is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.	
	As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.	
Bluetooth*	© 2005 Acer Inc. All rights reserved. Acer, the Acer logo and TravelMate are registered trademarks of Acer Inc. Other trademarks, registered trademarks, and/or service marks, indicated or otherwise, are the property of their respective owners.	
WIED	About Acer	
CERTIFIED CERTIFIED CISCO. Compatible	Acer ranks among the world's top five branded PC vendors, designing and marketing easy, dependable IT solutions that empower people to reach their goals and enhance their lives. In 2000, Acer spun-off its manufacturing operation to focus on globally marketing its brand-name products: desktop and mobile PCs, servers and storage, displays, peripherals, and e-business solutions for business, government, education, and home users. Established in 1976, the Acer Group employs	
SignalUp	5,600 people supporting dealers and distributors in more than 100 countries. Revenues in 2004 reached US\$7 billion. Please visit <u>www.acer.com</u> .	