

Extensa 7630EZ Specifications		
Operating system <sup>1</sup>	Genuine Windows Vista <sup>®</sup> Business (Service Pack 1)	
	Genuine Windows Vista <sup>®</sup> Home Premium (Service Pack 1)	
	Genuine Windows Vista <sup>®</sup> Home Basic (Service Pack 1)	
Platform <sup>1</sup>	Intel <sup>®</sup> Pentium <sup>®</sup> dual-core mobile processor T3200/T3400 (1 MB L2 Cache, 2/2.16 GHz, 667 MHz FSB, 35 W), supporting Intel <sup>®</sup> 64 architecture	
	Intel <sup>®</sup> Pentium <sup>®</sup> processor T4200 (1 MB L2 Cache, 2 GHz, 800 MHz FSB, 35 W), supporting Intel <sup>®</sup> 64 architecture	
	Mobile Intel <sup>®</sup> GL40 Express Chipset	
	Acer InviLink <sup>™</sup> Nplify <sup>™2,3</sup> , 802.11b/g/Draft-N Wi-Fi CERTIFIED <sup>®</sup> network connection, supporting Acer SignalUp <sup>™</sup> wireless technology	
	Acer InviLink <sup>™3</sup> 802.11b/g Wi-Fi CERTIFIED <sup>®</sup> network connection, supporting Acer SignalUp <sup>™</sup> wireless technology	
System memory <sup>1, 4, 5</sup>	Dual-channel DDR2 SDRAM support	
	Up to 2 GB of DDR2 667 MHz memory, upgradeable to 4 GB using two soDIMM modules <sup>6</sup>	
Display and graphics <sup>1</sup>	17" WXGA+ high-brightness (220-nit) Acer CrystalBrite <sup>™</sup> TFT LCD, 1440 x 900 pixel resolution, supporting simultaneous multi-window viewing via Acer GridVista <sup>™</sup>	
	17" WXGA+ high-brightness (220-nit), 1440 x 900 pixel resolution, supporting simultaneous multi-window viewing via Acer GridVista <sup>™</sup>	
	Mobile Intel <sup>®</sup> GL40 Express Chipset with integrated 3D graphics, featuring Intel <sup>®</sup> Graphics Media Accelerator 4500M (Intel <sup>®</sup> GMA 4500M) with up to 1759 MB of Intel <sup>®</sup> Dynamic Video Memory Technology 5.0 (64 MB of dedicated video memory, up to 1695 MB of shared system memory), supporting Microsoft <sup>®</sup> DirectX <sup>®</sup> 10	
	Dual independent display support	
	16.7 million colors	
	External resolution/refresh rate:	
	• 2048 x 1536: 75/60 Hz	
	• 1920 x 1440: 85/75/60 Hz	

Extensa 7630EZ Specifications		
	• 1920 x 1200: 75/60 Hz	
	• 1920 x 1080: 100/85/75/60 Hz	
	• 1680 x 945: 100/85/75/60 Hz	
	• 1600 x 1200: 120/100/85/75/60 Hz	
	• 1600 x 900: 120/100/85/75/60 Hz	
	• 1400 x 1050: 85/75/60 Hz	
	• 1366 x 768: 85/75/60 Hz	
	• 1280 x 1024: 120/100/85/75/60 Hz	
	• 1280 x 960: 85/75/60 Hz	
	• 1280 x 768: 85/75/60 Hz	
	• 1280 x 720: 100/85/75/60 Hz	
	• 1024 x 768: 120/100/85/75/60 Hz	
	• 800 x 600: 120/100/85/72/60 Hz	
	MPEG-2/DVD acceleration	
	WMV9 (VC-1) and H.264 (AVC) acceleration	
Storage subsystem <sup>1</sup>	One or two 120/160/250/320/500 GB or larger hard disk drives <sup>7</sup>	
	8X DVD-Super Multi double-layer drive:	
	<ul> <li>Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD+R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</li> </ul>	
	DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD+R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X	
	<ul> <li>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</li> <li>Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X</li> </ul>	
	<ul> <li>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</li> <li>Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM</li> </ul>	
	<ul> <li>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</li> <li>Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM</li> <li>DVD/CD-RW combo drive:</li> <li>Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 6X DVD-R, 6X DVD+R, 6X DVD-RW, 6X</li> </ul>	
Dimensions and weight <sup>1</sup>	<ul> <li>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</li> <li>Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM</li> <li>DVD/CD-RW combo drive:</li> <li>Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 6X DVD-R, 6X DVD+R, 6X DVD-RW, 6X DVD+RW, 4X DVD-RAM</li> </ul>	
	<pre>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</pre> Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM DVD/CD-RW combo drive: Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 6X DVD-R, 6X DVD+R, 6X DVD-RW, 6X DVD+RW, 4X DVD-RAM Write: 24X CD-R, 24X CD-RW 396 (W) x 286 (D) x 35.2/44 (H) mm (15.6 x 11.3	
	<pre>DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM</pre> • Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM DVD/CD-RW combo drive: • Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-RAM DVD/CD-RW, 6X DVD-R, 6X DVD+R, 6X DVD-RW, 6X DVD-ROM, 6X DVD-R, 6X DVD+R, 6X DVD-RW, 6X DVD+RW, 4X DVD-RAM • Write: 24X CD-R, 24X CD-RW 396 (W) x 286 (D) x 35.2/44 (H) mm (15.6 x 11.3 x 1.4/1.7 inches) 3.60 kg (7.93 lbs.) with 2 HDDs and 8-cell battery	

Extensa 7630EZ Specifications		
subsystem <sup>1</sup>	Standby and Hibernation power-saving modes	
	48.8 W 4400 mAh 6-cell Li-ion battery pack:	
	• 2-hour battery life <sup>8</sup>	
	3-pin 65 W AC adapter	
	ENERGY STAR <sup>®</sup> 4.0	
Input devices	105-/106-key keyboard with inverted "T" cursor layout, 2.5 mm (minimum) key travel	
	Touchpad pointing device	
	12 function keys, four cursor keys, two Windows <sup>®</sup> keys, hotkey controls, standard numeric keypad, international language support, independent US dollar and Euro symbol keys	
	Empowering Key	
	Easy-launch buttons: WLAN, Bluetooth <sup>®</sup> , email, Internet, programmable	
	Productivity keys: Lock, Presentation, Sync	
Audio	Two built-in Acer 3DSonic stereo speakers	
	High-definition audio support	
	MS-Sound compatible	
	Built-in microphone	
Communicatio n	Acer Video Conference <sup>1</sup> , featuring:	
	<ul> <li>Integrated Acer Crystal Eye webcam supporting enhanced Acer PrimaLite<sup>™</sup> technology<sup>1</sup></li> </ul>	
	• Optional Acer Xpress VoIP phone	
	WLAN <sup>1,3</sup> : Acer InviLink <sup>™</sup> Nplify <sup>™2</sup> 802.11b/g/Draft-N Wi-Fi CERTIFIED <sup>®</sup> network connection, supporting Acer SignalUp <sup>™</sup> wireless technology	
	WLAN <sup>1</sup> : Acer InviLink <sup>™</sup> 802.11b/g Wi-Fi CERTIFIED <sup>®</sup> network connection, supporting Acer SignalUp <sup>™</sup> wireless technology	
	WPAN <sup>1</sup> : Bluetooth <sup>®</sup> 2.0+EDR (Enhanced Data Rate)	
	LAN: Gigabit Ethernet supporting ASF (Alert Standard Format) 2.0, Wake-on-LAN ready	
I/O interface	Four USB 2.0 ports	
	External display (VGA) port	
	Headphone/speaker/line-out jack	
	Microphone-in jack	
	Line-in jack	

Extensa 7630EZ Specifications		
	Ethernet (RJ-45) port	
	DC-in jack for AC adapter	
Security	BIOS user, supervisor, HDD passwords	
	Kensington lock slot	
Software	Acer Empowering Technology (Acer ePower, eRecovery Management)	
	Acer Crystal Eye <sup>1</sup>	
	Acer GridVista <sup>™</sup>	
	Acer Launch Manager	
	Adobe® Reader®	
	Corel <sup>®</sup> WinDVD	
	McAfee <sup>®</sup> Internet Security Suite	
	Microsoft <sup>®</sup> Office Ready 2007	
	NTI Media Maker™	
	NTI Shadow <sup>™</sup>	
Options and accessories	Acer Xpress VoIP phone and Acer Video Conference Manager pack	
	512 MB / 1 GB / 2 GB DDR2 667 MHz soDIMM module	
	3-pin 65 W AC adapter	
	120/160/200/250/320/500 GB hard disk drive	
	USB optical mouse	
	External USB floppy disk drive	
System	Wi-Fi®	
compliance	ACPI 3.0	
	Mobile PC 2002	
	DMI 2.0	
Warranty	One-year International Travelers Warranty (ITW)	
Quality and reliability tests	Temperature and humidity	
	Hinge life	
	Weight and pressure	
	Acoustics	
	Spillage	
	Free drop	
	Shock and vibration	
	Electrostatic discharge immunity	
	Keyboard-switch life	
	MTBF (mean time between failures)	

## Extensa 7630EZ Specifications

Acer recommends Windows Vista® Business.

- 1. Specifications vary depending on model.
- 2. Acer InviLink<sup>™</sup> Nplify<sup>™</sup>, a high-throughput wireless solution, delivers superior performance and reliable connections while enabling emerging voice, video and data applications. Wi-Fi CERTIFIED<sup>®</sup>, it supports Acer SignalUp<sup>™</sup> wireless technology and is compliant with 802.11b/g/Draft-N and 802.11b/g standards.
- 3. Actual throughput may vary depending on network conditions and environmental factors such as network traffic or overhead, building construction and access point settings.
- 4. Up to 1 GB of available system memory may be allocated for system resource requirements.
- 5. Shared system memory may be allocated to support integrated graphics, depending on system memory size and other factors. Actual system memory available to the operating system will be reduced by the amount of dedicated and shared system memory utilized by the graphics solution and resources required by the operating environment.
- 6. A 64-bit operating system is required to enjoy the ultimate performance of 4 GB memory.
- 7. 1 GB equals 1 billion bytes. Actual formatted capacity is less and may vary depending on preloaded materials and the operating environment. Acer eRecovery Management utilizes up to 10 GB of the stated hard disk capacity as dedicated backup space.
- 8. Battery life varies depending on product specifications, computer settings, and applications or features launched, and may be reduced if Windows Aero<sup>™</sup> is enabled. All batteries' maximum capacity diminishes with time and use.
- 9. PTT countries: Asia: China, Hong Kong, Japan, Korea, Malaysia, Singapore, Taiwan. Europe: Austria, Belgium, Denmark, Finland, France, Germany, Greece, Holland, Iceland, Italy, Luxembourg, Norway, Portugal, Spain, Sweden, Switzerland. Oceania: Australia, New Zealand. N. America: Canada, USA.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

© 2008 Acer Inc. All rights reserved. Acer, the Acer logo, and Extensa are registered trademarks of Acer Inc. Other trademarks, registered trademarks, and/or service marks, indicated or otherwise, are the property of their respective owners.

Microsoft and Windows are registered trademarks of Microsoft Corporation. Intel and Pentium are registered trademarks of Intel Corporation.

## Extensa 7630EZ Specifications

## About Acer

Since its founding in 1976, Acer has constantly pursued the goal of breaking the barriers between people and technology. Focused on marketing its brand-name IT products around the globe, Acer ranks as the world's No. 3 vendor for total PCs and No. 2 for notebooks, with the fastest growth among the top-five players. A profitable and sustainable Channel Business Model is instrumental to Acer's continued growth, while the successful mergers of Gateway and Packard Bell complete the company's global footprint by strengthening its presence in the U.S., and enhancing its strong position in Europe. Acer Inc. employs 5,000 people worldwide. 2007 revenues reached US\$14.07 billion. See <u>www.acer.com</u> for more information.

