



Aspire 5536 Specifications	
Operating system¹	Genuine Windows Vista® Home Premium (Service Pack 1)
Platform¹	<p>AMD Better By Design program, featuring:</p> <ul style="list-style-type: none"> • AMD Turion™ X2 dual-core processor RM-72/RM-74/RM-75 (1 MB L2 cache, 2.10/2.20/2.20 GHz, DDR2 800 MHz, 35 W), supporting AMD HyperTransport™ 3.0 technology • AMD Athlon™ 64 X2 dual-core processor QL-62/QL-64/QL-65 (1 MB L2 cache, 2/2.10/2.10 GHz, DDR2 667 MHz, 35 W), supporting AMD HyperTransport™ 3.0 technology • AMD M780G Chipset • Acer InviLink™ Nplify™^{3, 4}, 802.11b/g/Draft-N Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology • Acer InviLink™ 802.11b/g Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology
System memory^{1, 5, 6}	<p>Dual-channel DDR2 SDRAM support</p> <p>Up to 4 GB of DDR2 667 MHz memory, upgradeable to 8 GB using two soDIMM modules for (for 64-bit OS)</p> <p>Up to 2 GB of DDR2 667 MHz memory, upgradeable to 4 GB using two soDIMM modules (for 32-bit OS)⁷</p>
Display	<p>15.6" HD 1366 x 768 pixel resolution, high-brightness (220-nit) Acer CineCrystal™ LED-backlit TFT LCD, supporting simultaneous multi-window viewing via Acer GridVista™</p> <p>16:9 aspect ratio</p> <p>8 ms high-def response time</p> <p>60% color gamut</p>
Graphics	<p>ATI Radeon™ HD 3200 Graphics with up to 2048⁸ MB of HyperMemory™ (256 MB of dedicated system memory, up to 1792 MB of shared system memory), supporting Unified Video Decoder (UVD), OpenEXR High Dynamic-Range (HDR) technology, Shader Model 4.0, Microsoft® DirectX® 10.0</p> <p>Dual independent display support</p> <p>16.7 million colors</p> <p>External resolution/refresh rate:</p>

Aspire 5536 Specifications

	<ul style="list-style-type: none"> • 2048 x 1536: 75/60 Hz • 1920 x 1440: 85/75/60 Hz • 1920 x 1200: 75/60 Hz • 1920 x 1080: 100/85/75/60 Hz • 1680 x 945: 100/85/75/60 Hz • 1600 x 1200: 120/100/85/75/60 Hz • 1600 x 900: 120/100/85/75/60 Hz • 1400 x 1050: 85/75/60 Hz • 1366 x 768: 85/75/60 Hz • 1280 x 1024: 120/100/85/75/60 Hz • 1280 x 960: 85/75/60 Hz • 1280 x 768: 85/75/60 Hz • 1280 x 720: 100/85/75/60 Hz • 1024 x 768: 120/100/85/75/60 Hz • 800 x 600: 120/100/85/72/60 Hz <p>MPEG-2/DVD decoding</p> <p>WMV9 (VC-1) and H.264 (AVC) decoding</p> <p>HDMI™ (High-Definition Multimedia Interface) with HDCP (High-bandwidth Digital Content Protection) support</p> <p>Acer Arcade™ Deluxe featuring Acer CinemaVision™ and Acer ClearVision™ technologies⁹</p>
<p>Audio</p>	<p>Dolby^{®10}-optimized surround sound system with two built-in stereo speakers</p> <p>Optimized 3rd Generation Dolby Home Theater^{®10} audio enhancement, featuring Dolby[®] Digital Live, Dolby[®] Pro Logic[®] IIx, Dolby[®] Headphone, Dolby[®] Natural Bass, Dolby[®] Sound Space Expander, Dolby[®] Audio Optimization, Dolby[®] High Frequency Enhancer technologies¹¹</p> <p>True5.1-channel surround sound output</p> <p>High-definition audio support</p> <p>S/PDIF (Sony/Philips Digital Interface)¹² support for digital speakers</p> <p>MS-Sound compatible</p> <p>Built-in microphone</p>

Aspire 5536 Specifications	
Storage	160/250/320/500 GB or larger hard disk drive ^{1, 13} 5-in-1 card reader, supporting Secure Digital™ (SD) Card, MultiMediaCard (MMC), Memory Stick™ (MS), Memory Stick PRO™ (MS PRO), xD-Picture Card™ (xD)
Optical media drive¹	4X Blu-ray Disc™/DVD-Super Multi double-layer drive: <ul style="list-style-type: none"> • Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 8X DVD-R, 8X DVD+R, 8X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD+R DL (double-layer), 8X DVD-RW, 8X DVD+RW, 5X DVD-RAM, 4X BD-ROM, 4X BD-R, 2X BD-RE, 4X BD-ROM DL (double-layer), 4X BD-R DL (double-layer), 2X BD-RE DL (double-layer) • Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM, 4X DVD+R DL (double-layer), 4X DVD-R DL (double-layer) 8X DVD-Super Multi double-layer drive: <ul style="list-style-type: none"> • Read: 24X CD-ROM, 24X CD-R, 24X CD-RW, 8X DVD-ROM, 8X DVD-R, 8X DVD+R, 6X DVD-ROM DL (double-layer), 6X DVD-R DL (double-layer), 6X DVD+R DL (double-layer), 6X DVD-RW, 6X DVD+RW, 5X DVD-RAM • Write: 24X CD-R, 16X CD-RW, 8X DVD-R, 8X DVD+R, 4X DVD-R DL (double-layer), 4X DVD+R DL (double-layer), 6X DVD-RW, 8X DVD+RW, 5X DVD-RAM
Communication	Acer Video Conference ¹ , featuring: <ul style="list-style-type: none"> • Integrated Acer Crystal Eye webcam supporting enhanced Acer PrismaLite™ technology • Optional Acer Xpress VoIP phone WLAN ^{1, 4} : Acer InviLink™ Nplify™ ³ 802.11b/g/Draft-N Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology WLAN ^{1, 4} : Acer InviLink™ 802.11b/g Wi-Fi CERTIFIED® network connection, supporting Acer SignalUp™ wireless technology WPAN ¹ : Bluetooth® 2.0+EDR (Enhanced Data Rate) LAN: Gigabit Ethernet, Wake-on-LAN ready Modem: 56K ITU V.92 with PTT approval ¹⁴ , Wake-on-Ring ready
Privacy control	BIOS user, supervisor, HDD passwords Kensington lock slot
Dimensions and	383 (W) x 250 (D) x 26/37 (H) mm (15.1 x 9.9 x 1.03/1.5

Aspire 5536 Specifications	
weight¹	inches) 2.8 kg (6.16 lbs.) with 6-cell battery pack
Power	ACPI 3.0 CPU power management standard: supports Standby and Hibernation power-saving modes 48.8 W 4400 mAh 6-cell Li-ion battery pack: <ul style="list-style-type: none"> • 3-hour battery life¹⁵ 2.5-hour rapid charge system-off, 3.5-hour charge-in-use 3-pin 65 W AC adapter ENERGY STAR® 5.0
Special keys and controls	103-/104-/107-key keyboard, with inverted "T" cursor layout, 1.8 mm (minimum) key travel Multi-gesture touchpad pointing device, supporting: <ul style="list-style-type: none"> • Circular-motion scrolling • Pinch-action zoom • Page flip 11 function keys, four cursor keys, two Windows® keys, hotkey controls, independent standard numeric keypad, international language support Easy-launch keys: Acer Backup, WLAN, Bluetooth® ¹ , programmable, volume up/down, touchpad lock Media keys (printed on keyboard): play/pause, stop, previous, next
I/O ports	5-in-1 card reader (SD™, MMC, MS, MS PRO, xD) Four USB 2.0 ports HDMI™ port with HDCP support External display (VGA) port Headphone/speaker/line-out jack with S/PDIF support Microphone-in jack Line-in jack Ethernet (RJ-45) port Modem (RJ-11) port DC-in jack for AC adapter

Aspire 5536 Specifications	
Software	<p>Acer Arcade™ Deluxe featuring Cinema, Album, Music, Acer HomeMedia, Online Media</p> <p>Acer Backup Manager</p> <p>Acer Recovery Management</p> <p>Acer Crystal Eye¹</p> <p>Acer GridVista™</p> <p>Acer GameZone</p> <p>Acer Game Console</p> <p>Adobe® Reader®</p> <p>Adobe Flash® Player</p> <p>Google Toolbar™</p> <p>Google Desktop™</p> <p>McAfee® Internet Security Suite</p> <p>NTI Media Maker™</p> <p>Microsoft® Works with Office Home and Student 2007 Trial (Service Pack 1)</p>
Optional items	<p>Acer Xpress VoIP phone and Acer Video Conference Manager pack</p> <p>1 GB / 2 GB DDR2 667 MHz soDIMM module</p> <p>6-cell Li-ion battery pack</p> <p>3-pin 65 W AC adapter</p> <p>External USB floppy disk drive</p>
Warranty	One-year International Travelers Warranty (ITW)
<p>Acer recommends Windows Vista® Home Premium.</p> <ol style="list-style-type: none"> 1. Specifications vary depending on model. 2. 64-bit software is required to enjoy the advantages of 64-bit processing. 3. Acer Nplify™, a high-throughput wireless solution, delivers superior performance and reliable connections while enabling emerging voice, video and data applications. Wi-Fi CERTIFIED®, it supports Acer SignalUp™ wireless technology and is compliant with 802.11a/b/g/Draft-N and 802.11b/g standards. 4. Actual throughput may vary depending on network conditions and environmental factors such as network traffic or overhead, building construction and access point settings. 5. Up to 1 GB of available system memory may be allocated for system resource requirements. 6. Shared system memory may be allocated to support integrated graphics, depending on system memory size and other factors. Actual system memory available to the operating system will be reduced 	

Aspire 5536 Specifications

by the amount of dedicated and shared system memory utilized by the graphics solution and resources required by the operating environment.

7. A 64-bit operating system is required to enjoy the ultimate performance of 4 GB memory.
8. For systems with 4 GB of system memory. The total graphics memory visible to the OS is less than the actual size allocated from the physical memory installed and varies depending on the configuration under a 32-bit OS.
9. Powered by CyberLink® technology.
10. Dolby® is a registered trademark of Dolby® Laboratories. Dolby Home Theater® is a trademark of Dolby® Laboratories.
11. Dolby® Pro Logic® and the double-D symbol are registered trademarks of Dolby® Laboratories.
12. Supports 7.1-channel surround sound and 2-channel stereo output (multiple streaming).
13. 1 GB is 1 billion bytes. Actual formatted capacity is less and may vary depending on preloaded materials and operating environment. Acer Recovery Management utilizes up to 10 GB of the stated hard disk capacity as dedicated backup space.
14. PTT countries: **Asia:** China, Hong Kong, Japan, Korea, Malaysia, Singapore, Taiwan. **Europe:** Austria, Belgium, Denmark, Finland, France, Germany, Greece, Holland, Iceland, Italy, Luxembourg, Norway, Portugal, Spain, Sweden, Switzerland. **Oceania:** Australia, New Zealand. **N. America:** Canada, USA.
15. Battery life varies depending on product specifications, computer settings, and applications or features launched, and may be reduced if Windows Aero™ is enabled. All batteries' maximum capacity diminishes with time and use.

In a continuing effort to improve the quality of our products, information in this document is subject to change without notice. Images shown are only representations of some of the configurations available for this model. Availability may vary depending on region.

As a phenomenon known to thin-film transistors (TFTs), liquid crystal displays (LCDs) commonly exhibit a small number of discoloration dots, as so-called "non-conforming pixels." This phenomenon is a limitation of TFT LCD technology, not a product defect, and as such is not covered by Acer's warranty.

© 2009 Acer Inc. All rights reserved. Acer, the Acer logo, and Aspire are registered trademarks of Acer Inc. Other trademarks, registered trademarks, and/or service marks, indicated or otherwise, are the property of their respective owners.

Microsoft and Windows are registered trademarks of Microsoft Corporation.

About Acer

Since its founding in 1976, Acer has constantly pursued the goal of breaking the barriers between people and technology. Focused on marketing its brand-name IT products around the globe, Acer ranks as the world's No. 3 vendor for total PCs and No. 2 for notebooks, with the fastest growth among the top-five players. A profitable and sustainable Channel Business Model is instrumental to Acer's continued growth, while the successful mergers of Gateway and Packard Bell complete the company's global footprint by strengthening its presence in the U.S., and enhancing its strong position in Europe. Acer Inc. employs 5,000 people worldwide. 2007 revenues reached US\$14.07 billion. See www.acer.com for more information.

Aspire 5536 Specifications

